

DS-PM1-O4H-H Wired 4-way power relay expander

114-506



DS-PM1-O4H-H is a wired 4-way power relay expander. The expander connects directly to the 100 V~240 V source and closes/opens the circuit on command via Speed-X from the AX Hybrid Pro control panel. Each relay can handle current of up to 16A, which is enough to connect a very power-hungry device.

- Supports 4 onboard power relays, each relay can handle current of up to 16A
- Powered by Speed-X technology, supporting expander cascading with 1 uplink Speed-X port and 1 downlink Speed-X port

▪ Specification

Hardware features	
Serial port	1 TTL serial port
Tamper-Proof	Support (front and rear)
Bus	2×Speed-X bus, 1 uplink for control panel connection and 1 downlink for next expander
Electrical characteristics	
Power supply	9 to 24 VDC, 1A
Power consumption	Maximum current 210 mA@12 VDC; Quiescent current 65 mA@12 VDC
Display	
LED Indicator	1 for power, or fault
General	
Dimension(WxHxD)	110 mm × 155 mm × 32.5 mm
Shell material	Plastic
Weight	333.1 g
Operation temperature	-10 °C to 40 °C
Operation humidity	10% to 90%

ORDERING INFORMATION

114-506

Hikvision DS-PM1-O4H-H Output Expander 4 Relays (Hi)



Innovative Electronic Solutions
www.ness.com.au



NSW Ph 02 8825 9222
sales@ness.com.au

VIC Ph 03 9875 6400
nessmelb@ness.com.au

QLD Ph 07 3399 4910
nessbris@ness.com.au

WA Ph 08 9328 2511
nessper@ness.com.au

SA Ph 08 8152 0000
adelaide@ness.com.au